

60W/80W/100W/150W/200W/300W



camping;road works;large scale outdoor event;construction lighting

Features

It's also a compact solution for your work area lighting. Ease of use translate to portability and quick deployment.

This light balloon features a compact and flexible design that quickly provides light where you need it. Thanks to its simple construction, set up of the light is quick and easy.

- Hihtlingt LED chips
- Optional remote controller
- UL listed power supply(IP 67)
- Aluminum alloy coat
- Energy efficient, low heat output
- Silent running
- Excellent heat dissipation
- 360°llumination

- Enhanced light penetration
- Easy Installation
- 50,000 hour lifespan
- plug and play
- With a variety of installation
- Lightweight slimline design
- Easy clip on bars
- Ip65 waterproof, Use in moist environment

Product picture



MODEL: BB-HJD-XXXW-B1

	DATA SHEET(lamps)						
Power	60W	80W	100W	150W	200W	300W	
Model	BB-HJD-60W-B1	BB-HJD-80W-B1	BB-HJD-100W-B1	BB-HJD-150W-B1	BB-HJD-200W-B1	BB-HJD-300W-B1	
Luminous Flux	9600lm	12800lm	16000lm	24000lm	32000lm	48000lm	
Dimension(mm)		Ø500xH468					
Net weight		20.3kg 360°					
Beam Angle							
Materials	Aluminum alloy+Soft cloth 160lm/w						
Luminous Efficacy							
Operation Temp	-40 to +45°C						
ССТ	2700K SW / 3000K WW / 4100K NW / 5000K DW / 5700K CW / 6500K SCW						
CRI	80+						
Life Span		50,000 hours at 25°C					
Voltage	100-277VAC/24V DC						
Driver		Built-in power supply Optional					
Dimming							
Cover	Soft cloth						
Luminous Source	SMD LED						
IP Rating	IP 65						
PF	>0.95						
Installation	Tripod mounting/Pole mounting						
Warranty	3 Years						

	Tripod	
Style	3M Tripod hand-operated	4.3M Tripod hand-operated
Height(min-max)	1600-3000mm	1700-4300mm
Weight(kg)	13.2	15.5


Order information

Model:BB-HJD-XXXW-B1

А	В	С	D	E	F	G	Н
Rated power	Input voltage	Control mode	Dimming	сст	LED CHIP	Tripod	Color
60W 80W 100W 150W 200W 300W	Blank- 100-277VAC Optional- 24VDC	Blank- Switch Optional- Remove control	Blank-without Optional- Dimmable	2700K SW / 3000K WW / 4100K NW / 5000K DW / 5700K CW / 6500K SCW	Blank- 3030 SMD	Blank-3m Optional– 4. 3m	Blank- Black

Dimensional drawing


There is a slight error in manual measurement



3m tripod

4.3m tripod

Surface Of Intensity Distribution



Application case

LED blloon light be widely applied in daily life. Such as Temporary work lighting, road maintenance, outdoor rescue, outdoor activities, picnic camping and more

1.Construction. 2.Camping 3.Filming 4.Sporting Events 5.Roadworks6.Infrastructure 7.Photography 8.Renovation 9.Search/Rescue







Remote Control

*The remote control is not provided by default, If you need, please contact sales.





Remote control RC01

◆ ON/OFF * Press the "ON/OFF" button, the light keeps permanently on or off.

* Press "Auto Mode", "RESET" or "Scene mode" buttons to quit from this mode.

Auto Mode

* Press "Auto Mode" button, the sensor starts to work and all settings remain the same before the light gets switched on/off.

* Press "RESET" button, products with DIP switch will be controlled by DIP switches.

Scene Mode

Scene Mode	Detection	Hold-time	Daylight	Stand-by	Stand-by
			threshold	period	dimming level
Sc1	100%	30s	2Lux	1min	10%
Sc2	100%	5min	10Lux	10min	10%
Sc3	100%	10min	50Lux	30min	10%
Sc4	100%	30min	Disable	+∞	10%

Test

* The button "Test (2s)" is for testing purpose after commissioning. Pressing this button, the sensor goes to test mode(hold time is only 2s) automatically, stand-by period and daylight sensor are disabled.


This mode can be ended by pressing "reset", "Auto mode" scene mode" or "hold time". The sensor setting is changed accordingly.

Brightness settings: Disable.

Test mode can press any key to exit this mode.

On/off control	There are 4 fixed scene modes program built-in the remote control to choose for different applications,
Detection area	Press the button "detection range" to set detection range as 100% / 75% / 50% / 10%.
Hold-time	Press the button"hold-time" to set hold-time as 5s / 30s / 1min / 3min / 5min / 10min /20min/ 30min .
Daylight threshold	Press the button "daylight sensor" to set daylight threshold as 2Lux/10Lux/30Lux/50Lux/80Lux/120Lux/disable.

Remote control RC02



Function:

- * Wireless remote control, you can remotely control the light switch.
- * Can control the lights of 4 groups of channels, each group is independent.

 Multiple lights can be set for each group.
- * The remote control distance is 10-20m.
- * Dimming function, you can increase and decrease the brightness of the lamp.
- * Must be used with dimming driver.

Note:

- * The work light without sensor and the work light with sensor can be equipped with RC02 remote control.
- * Only work light with sensor can be equipped with RC01 remote control.

Package

Item	Packaging	Carton Size(cm)	G.W
3m tripod	1pc/CIN	165*24*20	20kg
4.3m tripod	1pc/CTN	175*24*20	23kg